



Programming Daylight Saving Time on the Digia II Digital Video Recorder

For customers who have the Digia II recorders, the units have been designed with the new Daylight Saving Time changes in mind. A qualified Installer or Service person must change these programming settings. There are two ways to make the change, one is from the front panel and the other is from the Digia II web interface.

To change these settings from the front panel, perform the following operations:

1. Enter Installer programming on the unit.
2. Using the UP and DOWN arrows highlight the System menu item, number 7, and press ENTER.
3. When the System Menu opens, press ENTER again. You should see the Date/Time Format field highlighted.
4. Use the DOWN arrow to highlight the Daylight Savings checkbox. If this box is unchecked, press ENTER to check it.
5. Use the DOWN arrow to move to the Start On month and press ENTER. You should now see the month highlighted with a purple color. Press the DOWN arrow to change the month selection to MAR.
6. Now press the RIGHT arrow to move the purple highlight to the area of selecting the week. Use the DOWN arrow to change the week selection to 2ND and press ENTER.
7. Use the DOWN arrow to move to End On week and Press the ENTER button. You should now see the End On week highlighted in Purple. Press the UP arrow to change the week to 1ST.
8. Use the Left arrow to move to the End On month, and the UP arrow to change it to NOV. Press the ENTER button to save changes.
9. Press the MENU button to exit programming. The unit is now configured for the new Daylight Saving Time start and stop dates.

To change these settings from the Digia II Browser interface, perform the following operations:

1. Using Internet Explorer, connect to the unit. When the Digia II Browser interface appears you will need to select "Admin" for the "Login As" selection. Then enter the Network Pass Code and Admin Pass Code. Then click on OK. (Refer to the User Manual for instructions on how to access the Digia II Browser interface if needed)
2. When the main screen appears you should see the quad video screen and the control panel section on the right. In the control panel section click on the CONFIGURATION tab.
3. Then, click on the SYSTEM icon located on the bottom left below the CONFIGURATION tab.
4. In the System Date&Time section make sure the "Daylight Saving" check box is checked.
5. In the Start On setting select "Mar" for the month and 2nd for the week.
6. In the End On setting select "Nov" for the month and 1st for the week.
7. All other setting should be correct. Click on the APPLY button. The unit is now configured for the new Daylight Saving Time start and stop dates.